

1 - Provide a drilling template:

Reference	HAS	B	VS	
ES0501313	130	130	78	mm
ES0501313	195	195	78	mm
ES0802020	196	130	78	mm
ET0501913	266	130	78	mm
ET1002713	Ø130		78	mm
ER05013	Ø196		78	mm
ER08019			78	mm

2- Insert the recessed box into the wall


3 - For the electrical connection use a power cable compliant with 60227IEC 52/EN50525.

4- Connect the board to the electrical network with a cable with a section of 0.75mm².

5- Fix the plate and the light fixture with the screws provided as accessories

6 - Clip the light fixture onto its base

7 - Check that the luminaire is maintained correctly


 This symbol indicates that this product must not be disposed of with normal household waste according to European legislation 2012/19/EU. To limit the risks to the environment and health caused by the uncontrolled discharge of waste and to promote the reuse of these materials, products must be recycled. To do this, use the collection networks in your region or contact your retailer.

Fixture maintenance:

- 1) Cut off the power supply
- 2) With a dry antistatic cloth, dust the diffuser and the casing without open the product. This can guarantee better yield and reduce the consumption of the luminaire.

End of life:

- 1) Turn off the power supply.
- 2) Remove the luminaire(s) from its mounting support
- 3) Contact your town hall to locate collection centers

 The LED modules fitted to the product cannot be replaced by the installer or the user. Only the manufacturer or an organization authorized by the latter are authorized to carry out the replacement. The Manufacturer reserves the right to replace the defective module free of charge.

This product must be installed by a qualified person.
Ensure product compatibility depending on its environment.
The installation of the device must be done according to the rules of the art. We disclaim all liability and reserve the right to void the warranty. luminaire in the event of non-compliant installation, not respecting the recommendations, or modifying the characteristics of the device. Keep this document for any future utility.

Environmental Protection (W.E.E.E.) – Aurora's WEEE Reg.No. WEE/BG0130YX (UK Only)

 Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Aurora does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Aurora product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his take back of the product for the correct disposal.

GUARANTEE

This product is guaranteed for a period of 5 years from the date of purchase. The guarantee is invalid in the case of improper use, installation, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the guarantee period it will be replaced free of charge, subject to correct installation and return of the faulty unit. Aurora does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Aurora reserves the right to alter specifications without prior notice.

301820, 301821, 301822, 301823, 301824, 301825