


Installation Engineers Contact Details:			Luminaire Ref / Location								
Name:		Tel:									
Luminaire Details:			Full Recharge Duration 24Hours		Duration: 3hrs		Lamp Type:				
ROUTINE TEST RECORD											
Test Type	Year 1		Year 2		Year 3		Year 4		Year 5		
	Signed	Date	Signed	Date	Signed	Date	Signed	Date	Signed	Date	
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
Functional											
3hr Duration											

### Dimensions:

Part No.	Description	L (mm)	W (mm)	D (mm)	Weight
430962	Grafham Plug & Play Linear Internal 2W Emergency Pack with E-Sel3	184	54	32	250g



### End Of Life Disposal:

Disassembly instructions for end of life disposal available on website.  
 Disposal of Electronic Equipment WEEE Directive 2002/96/EC This product falls within the scope of the Waste Electrical & Electronic Equipment Directive (WEEE), which means the product should not be disposed of as normal household waste. Please recycle where facilities exist or check with your Local Authority. RoHS - All components and materials used in this product are RoHS 2002/95/EC compliant. Specifications may change from time to time. The information contained in this leaflet is for guidance only and should not be considered as always accurate and should be treated as not representative.

## Installation Instructions



## Grafham Emergency Pack



<b>Input</b>	220-240V AC 50/60Hz
<b>Power</b>	2W
<b>Operating Temp</b>	0-60°C
<b>Battery</b>	3.2V LiFePO4 3200mAh
<b>Recharge Time</b>	24Hrs
<b>Function</b>	Self-Test / Manual Test
<b>Light Source Energy Rating</b>	N/A



### Box Contents:

- Emergency Pack



Selectable  
Emergency



Class  
II



Ingress  
Protection

### Tools Required For Installation:

- N/A



**READ THESE INSTRUCTIONS THOROUGHLY BEFORE INSTALLATION  
 KEEP THESE INSTRUCTIONS FOR FUTURE REFERENCE.**

### IMPORTANT:

This product must be installed by a qualified electrician or competent person, and in accordance with current building and IET wiring regulations.

### Warranty:

This product is warranted for a period of 5Years from the date of purchase\*\*. The backup battery pack in the emergency version is warranted for a period of 5 Years. The warranty could be invalidated should the product not be installed according to these instructions, outside the scope of the specification or the product has been altered or tampered with in any way. Please see website for terms and conditions.



**WARNING: Risk of electric shock!**  
**Isolate the mains power before proceeding.**

- Turn off the mains power before performing inspections, installation, or removal
- Verify that the supply voltage is correct by comparing it with the luminaire label information
- It is the installers responsibility to ensure installation is suitable for the total load of the luminaire(s). The supply cable, fuses/circuit breakers must be correctly rated for the electrical load and considering for any transient inrush currents that may occur.
- Do not perform insulation strength or resistance tests on installed luminaire(s) connected

**Wiring instructions for units equipped an with EMERGENCY function:**

Emergency lighting luminaries must be installed and maintained in accordance with the emergency lighting standard BS 5266-1

- For the emergency unit to work correctly, please ensure that an uninterrupted permanent live feed is present and is connected directly to the 'Permanent Live' terminal of the mains terminal block. Please ensure there are no switches, PIRs etc within the permanent live feed, constant switching of the emergency pack could result in premature battery failure.
- Following power up the green LED indicator should illuminate to indicate charging. If power to the unit is disrupted or isolated, the unit indicating green LED will switch off, triggering the emergency LEDs to illuminate.
- When self-test mode is selected, 24hrs from connection to mains power, a 3hrs duration test will be performed automatically.

**Installation Procedure:**

1. Fit emergency pack as shown with mains (sleeved) cables facing terminal block.
2. Disconnect cable connectors between terminal block and driver.
3. Join the connectors as shown: terminal block to emergency pack Input, driver to emergency pack output.
4. Disconnect driver output to LED's connectors.
5. Join the connectors as shown: LED's to emergency pack DC output, driver DC output to emergency pack DC input.
6. Install the emergency LED indicator bezel into the housing first, then push the LED indicator into it.
7. Connect the battery lead & select the emergency mode as shown.
8. Reconnect mains supply.

**Emergency Indication:**

	Colour	LED Indication	Status
	Green	Permanent Green	Normal Function
	Green	Fast Flashing Green (0.1 sec on, 0.1 sec off)	Function Test In Progress
	Green	Slow Flashing Green (1 sec on, 1 sec off)	Duration Test In Progress
	Red	Permanent Red	Load Failure
	Red	Slow Flashing Red (1 sec on, 1 sec off)	Battery Failure

To reset unit after failure, press and hold button attached to emergency pack for 5 seconds .

