

## Installation Instructions: Quick Fix Connector (08198)

### Important Information

**We recommend that luminaires are installed by a qualified electrician ensuring the installation complies with current IEE wiring regulations BS7671:2018 & local building control.**

- BELL will not accept responsibility for any claims arising from a poor installation..

### Important User Advice


- Always switch off mains supply before installing.

This product may contain substances that can be hazardous to the environment if not disposed of properly. Electrical and electronic equipment should never be disposed of with general household waste but must be separated for its correct treatment and recovery.

Where possible recycle your packaging.







20A / 250v



Live: Brown  
Earth: Yellow/Green  
Neutral: Blue  
L1: Auxillary  
Lo: Loop

### Female Socket

Up to 3 x 2.5mm<sup>2</sup> flat twin and earth cables can be used



### Male Plug

Up to 1.5mm<sup>2</sup> flexible 3 core cable can be used

**British Electric Lamps Ltd**

Unit A Foxbridge Way, Normanton Industrial Estate  
Normanton, West Yorkshire. WF6 1TN

T: +44 (0)1924 893380 F: +44 (0)1924 894320 E: sales@bellighting.co.uk

[www.bellighting.co.uk](http://www.bellighting.co.uk)



## Installation Instructions: Quick Fix Connector (08198)

**Read these instructions before installation and retain for future reference. This equipment should be installed by a competent electrician** ⚠️

### Preparation

Before commencing any electrical work ensure the mains isolator on the consumer unit is in the **OFF** position, to prevent the possibility of electric shock.

These couplers are suitable for installation in **NON-READILY** accessible areas.

Any dangerous compatibility between different manufacturer installation coupler system is not automatically prevented by compliance with IEC 61535.

This system is NOT a replacement for a domestic plug and socket outlet system.

### Installation

Remove cover as shown overleaf.

Strip cables back to the appropriate lengths. (Earth must be 8mm longer than the Live & neutral)

Offer cable to the terminal, ensuring there are no stray strands of wire.

Screw down tight on to the cable, make sure the cable cannot be pulled out.

Press the cables into the clamps & replace cover.

Lock cover in to place.

**Technical Helpline +44 (0)1924 893380**

**www.bellighting.co.uk**