

LED High Output T8 Tube

- Suitable to replace both switch start and high frequency
- Designed to replace conventional fluorescent tubes
- Cost effective and energy saving
- 160Lm/W LED High Output T8
- Long life up to 50,000 hours
- Emergency pack available
- Up to 67% energy savings
- Low maintenance costs
- Simple Retrofit



5 Year Silver Warranty

Code	Lamp Type	Temp	Lm	ØxL (mm)
Non Dimmable				
60237	8.5W LED T8 Tube, G13	4000K	1360	28x600
60238	13W LED T8 Tube, G13		2080	28x900
60239	16W LED T8 Tube, G13		2560	28x1200
60240	21W LED T8 Tube, G13		3360	28x1500
60241	23W LED T8 Tube, G13		3680	28x1800
09125	Emergency Pack - Self Test On/Off Switch	-	-	-
For use with magnetic ballast: Remove starter and capacitor		-	-	-
For use with electronic ballast: Remove control gear and wire directly to mains		-	-	-
Emergency versions must be tested in line with the requirements of B55266, failure to do so may effect battery life and warranty.				



Energy Savings compared to old technology CFL Lamps

8.5W $\frac{18}{W}$ Energy Saving 53%	13W $\frac{30}{W}$ Energy Saving 56%	16W $\frac{36}{W}$ Energy Saving 55%	21W $\frac{58}{W}$ Energy Saving 63%	23W $\frac{70}{W}$ Energy Saving 67%
Quality Assured Product Warranty ² 5 Year	Colour Rendering Index ² 80	Lumens Maintenance Ratio ¹ 80	Operating Hours 50,000	



