

LED Wattage Switchable CCT T8 Tube

- Suitable to replace both switch start and high frequency
- Designed to replace conventional fluorescent tubes
- Cost effective and energy saving
- Long life up to 500,000 hours
- Emergency pack available
- Up to 65% energy savings
- Low maintenance costs
- Simple Retrofit
- LED CCT T8



5 Year Silver Warranty

Code	Lamp Type	Temp	Lm	ØxL (mm)
Non Dimmable				
60260	5/9W Wattage Switchable LED T8 Tube - CCT, 600mm (2ft)	3/4/6000K	700-1250	28x600
60261	9/17.5W Wattage Switchable LED T8 Tube - CCT, 1200mm (4ft)		1250-2450	28x1200
60262	12/22W Wattage Switchable LED T8 Tube - CCT, 1500mm (5ft)		1680-3100	28x1500
60263	12/24W Wattage Switchable LED T8 Tube - CCT, 1800mm (6ft)		1700-3350	28x1778
09125	Emergency Pack for LED Tubes - Self Test On/Off Switch	-	-	-
50561	Starter for LED Tube	-	-	-

For use with magnetic ballast: Remove starter and capacitor

For use with electronic ballast: Remove control gear and wire directly to mains



Energy Savings compared to old technology CFL Lamps



