

# SYCAMORE

## Installation instructions: 5m IP20 Uncoated Flexible LED STRIP SY8982NW/WW

Thank you for purchasing this SycamoreLED.com product. Please make sure instructions are followed carefully prior to and during installation and product is not altered, otherwise warranty may not be valid. For technical support or warranty information please visit [www.sycamoreLED.com](http://www.sycamoreLED.com), or call our dedicated technical helpline +44 (0) 113 2866686.

### IMPORTANT—Please read prior to installation

- 1) Please read these instructions carefully before commencing any work
- 2) Please retain these instructions for future reference
- 3) It is strongly recommended that this unit is installed by a qualified electrician in accordance with the IEE wiring regulations and building regulations
- 4) To prevent electrocution switch the power off at the mains supply before installing or maintaining this fitting
- 5) Ensure others cannot restore the electrical supply without your knowledge
- 6) The PSU must be rated 12VDC and be compatible with the pre-wired connector system of this product
- 7) Never exceed the wattage stated
- 8) Locate driver (IP20) in an unclassified zone

### INSTALLATION

- 1) **IMPORTANT:** Before installation of any flexible LED strip, the surface to which it is being installed upon must be cleaned with white spirit or similar to ensure adhesion.
- 2) **FLEXIBLE LED strip** can be installed by applying VHB 3M tape, or by fitting into an aluminium profile
- 3) The strip is pre-wired with a 2m cable and connector at each end to allow any cut off pieces to be re-used.
- 4) The strip cannot be twisted, dropped or left hanging
- 5) Locate in desired location and make sure that each cable/connector can be connected to a relevant PSU.
- 6) Ensure the strip is secure along its length
- 7) Restore power and test for operation

### CUTTING

- 1) The strip can be cut to length, at 50mm intervals.

### CARE IN USE

- 1) Please note this fitting has non replaceable parts
- 2) Always switch off or disconnect from the mains when cleaning the product.
- 3) We recommend cleaning with a soft dry cloth. Do not use scourers, abrasives or chemical cleaners.
- 4) Do not allow moisture to come into contact with electrical parts
- 5) This luminaire should not be disposed of with normal household rubbish. When a replacement is purchased, this luminaire should be returned to the retailer to safely dispose of (WEEE Directive effective July 2006—Waste from Electrical & Electronic Equipment).

### NOTES

Power Supply - 12VDC  
Cable Length - x2 2m Wattage -  
4W Per Metre  
IP Rating - IP20  
Cut Marks - Every 50mm  
LED per metre - 60  
3M VHB (Very High Bond) Tape  
Re-Connecting Cable Available

SycamoreLED.com

LS25 2DY

Technical helpline : 0113 2866686

\*Please email [sales@sycamoreled.com](mailto:sales@sycamoreled.com) to register your product

