

# Lumineux

MAKING LIGHT WORK



## Eyebrook Surface LED Downlights Standard Versions



**READ THESE INSTRUCTIONS THOROUGHLY BEFORE  
INSTALLATION KEEP THESE INSTRUCTIONS FOR FUTURE  
REFERENCE**

**IMPORTANT:** This product must be installed by a qualified electrician or competent person,  
and in accordance with current building and IET wiring regulations.

**GENERAL:** This lighting fixture is designed for permanent connection to fixed wiring which must have suitable circuit protection by the means of the appropriate MCB or fuse.

The product is suitable for installation on surfaces with normal flammability e.g. wood, plasterboard and masonry. It is not suitable for highly flammable surfaces such as polystyrene or textiles.

LED Chips can be susceptible to damage by vapours, gases, etc emitted by other materials, especially rubber, which can cause a reduction in light output performance.

DO NOT introduce any parts such as alternative grommets etc. to the inside of this fixture, other than those that have been provided. Failing to observe this and any damage caused thereby, may invalidate the warranty.

**MAINTENANCE:** To avoid personal injury or damage to equipment, disconnect the power to the light fitting before conducting any maintenance

**WARNING:** No user serviceable parts inside of the fixture, risk of electric shock. Clean the lens periodically as needed to ensure continued light output performance. Clean only with non-abrasive cloth if required.

**WARRANTY:** This luminaire is warranted for a period of 5 years from the date of purchase. The warranty could be invalidated should the light fitting not be installed according to these instructions, outside the scope of the specification or the product has been altered or tampered with in any way. Please see website for terms and conditions.

### Product Specification:

Model No.	Eyebrook Surface
Input Voltage:	220 240V AC
Operating Temp Standard:	0°C to +40°C
Operating Temp Emergency:	N/A
IP Rating:	IP54 (front of product)



Manby Business Park, Manby, Lincolnshire, LN11 8UT  
Lumineux is a B&T Associates Ltd company.



[www.lumineux.co.uk](http://www.lumineux.co.uk)

**DISPOSAL:** The light source of this unit is not replaceable; when the light source reaches its end of life the whole luminaire shall be replaced.

Disposal of Electronic Equipment WEEE Directive 2002/96/EC This product falls within the scope of the Waste Electrical & Electronic Equipment Directive (WEEE), which means the product should not be disposed of as normal household waste. Please recycle where facilities exist or check with your Local Authority . RoHS – All components and materials used in this product are RoHS 2002/95/EC compliant.  
\*Specifications may change from time to time. The information contained in this leaflet is for guidance only and should not be considered as always accurate.

**UNPACKING:** This lighting fixture has been properly packed to avoid damage during transit. Before commencing with the installation carefully inspect the luminaire to confirm there is no damage. **DO NOT INSTALL** if any damage has occurred to the fixture or any of its components.

**CARTON CONTENTS:**        - Fixture        - Instruction Sheet

**INSTALLATION:**



**WARNING: Risk of electric shock! Isolate the mains power before proceeding.**

IMPORTANT - Please ensure that there is an adequate free flow of air around the light fitting including the driver and it is not covered with any insulating material.

1. Hold the tab on the back of the fixture, rotate anti-clockwise and pull out the bracket
2. Secure the bracket into desired location using suitable fixings
3. Wire mains connection into terminal as below.
4. Connect the retaining cable and all wire connections
5. Re-fit the light to the bracket by rotating clockwise to lock into place.
6. Re-connect the mains supply.

