

## FOR SELF TEST AND EMERGENCY

**SELF TEST METHOD:** Please ensure this product is tested every Month (every 30 days, lasts for 10 seconds), and every Half-Year (every 180 days, lasts for 3 hours).

MODE	METHOD FOR MODE	IF	LED INDICATOR STATUS	BEEP SOUND	RESULT
Mains ON	No action needed	No faults	Green (Permanently On)	OFF	Green LED
	No action needed	Battery fault	Red (Flashes every 1 Hz)	Beep every 45 seconds	Red LED, Loud Beep sound
	No action needed	LED fault *	Amber (Flashes every 1 Hz) *	Beep every 45 seconds *	Amber LED, Loud Beep sound *
Monthly self test battery discharge (discharges the battery for 10 seconds)	Monthly test mode: Hold test button for 3 seconds, 2 beeps.	Battery Ok	All indicators OFF	OFF	Green LED
		Battery fault	Red (Flashes every 1 Hz)	Beep every 45 seconds	Red LED, Loud Beep sound
		LED fault	Amber (Flashes every 1 Hz)	Beep every 45 seconds	Amber LED, Loud Beep sound
Half-Year self test battery discharge (discharges the battery for 3 hours)	Yearly test mode: Hold test button for 6 seconds, 3 beeps.	Battery Ok	All indicators OFF	OFF	Green LED
		Battery fault	Red (Flashes every 1 Hz)	Beep every 45 seconds	Red LED, Loud Beep sound
		LED fault	Amber (Flashes every 1 Hz)	Beep every 45 seconds	Amber LED, Loud Beep sound
Mains Failure	No action needed Luminaire enters 3 hour emergency mode	Battery Ok	All indicators OFF	OFF	

**NOTE:**

- No AC power will cause luminaire to enter Emergency mode.
- After a repair, please connect AC power and perform a test (for performance confirmation). To do this operate the test switch for 1 second.
- If the battery and LED board failure simultaneously, the red LED will flash.
- Any beep sound will stop after a fix.
- Manual testing will not affect the monthly and half-yearly testing schedule.

# ENLITE®

**CODE: WP1/CWS**  
COLOUR AND WATTAGE SWITCHABLE  
WALLPACK




## IMPORTANT INSTALLATION INFORMATION

- Installation should be carried out by a qualified electrician in accordance with the latest edition of the National wiring regulations.
  - Mains supply voltage 220-240V AC 50/60Hz
  - Ensure that ALL electrical connections are tight with no loose strands including factory made connections.
  - Class II, Double Insulated an earth is not required.
  - IP65 protected against dust and jets of water. They are suitable for installation in locations containing a bath or shower, as defined by the National Wiring Regulations, Zones 1 & 2 where water jets are likely.
  - There are no replaceable parts in this luminaire.
  - These luminaires are not dimmable.
  - This product is rated to IK10
  - This product contains a light source of energy efficiency class E.
- 
- LIVE – (Brown) to Terminal Marked L  
NEUTRAL – (Blue) to Terminal Marked N
  - Photocell version is activated at: On (20 lux) Off (>60 lux)
  - Torq settings for screws are 1.2mm

## WARRANTY INFORMATION

Environmental Protection (W.E.E.E.) – Enlite's WEEE Reg.No. WEE/BG0130YX (UK Only)

 Waste Electrical & Electronic Equipment Regulations (WEEE) requires that any of our products showing this marking (left) must not be disposed of with other household or commercial waste. Enlite does not levy any WEEE disposal charges to its customers for affected WEEE related products. To prevent possible harm to the environment or human health from uncontrolled waste disposal, please separate any such product from other waste types and recycle it responsibly at your local facilities. Check with your Local Authority, Recycling Centre or retailer for recycling advice. If, when you purchased any Enlite product, your supplier included a WEEE disposal fee, you should then contact your supplier for advice on his take back of the product for the correct disposal.

## GUARANTEE

This product is guaranteed for a period of 3 years from the date of purchase. The guarantee is invalid in the case of improper use, installation, tampering, and removal of the Q.C. date label, installation in an improper working environment or installation not according to the current edition of the National Wiring Regulations. Should this product fail during the guarantee period it will be replaced free of charge, subject to correct installation and return of the faulty unit. Enlite does not accept responsibility for any installation costs associated with the replacement of this product. This warranty is in addition to the statutory rights in your country of purchase. Enlite reserves the right to alter specifications without prior notice.