

## Asymmetric/Symmetric LED CCT Switchable Floodlight

- Super Sleek Compact Design for seamless integration with the surroundings
- Colour selectable 3000K / 4000K / 5000K
- Versatile Angled Adjustable Bracket
- Tempered reinforced glass cover: better optical and thermal performance
- Ease of maintenance: Replaceable Driver/LED Module/Lens
- Hinged Glass Cover: up to 100° folding angle
- Optional Easy Fit PIR sensor (10-50W only)
- Pre-wired with 1m lead (10-50w) & 1.5m (100-300W)
- Built-in Surge Protection 2KV (10-50w), 6KV (100-200W) & 10KV (300W)
- Quick installation: patented 'Removable Bracket Clamp' design (100-200W)
- Built-in Photocell options available (100-300W only)


Plug In PIR  
(10-50W Versions)



Quality Assured Product Warranty <sup>1</sup> <b>7 Year</b>	On site Warranty <sup>2</sup> <b>2 Year</b>	Colour Rendering Index <sup>3</sup> <b>80</b>	Lumens Maintenance Ratio <sup>4</sup> <b>L80 B10</b>	Water & Dust Protected <b>IP65</b>	Impact Rating <b>IK08</b>	Operating Hours <b>50,000</b>
--	--	--	---	---------------------------------------	------------------------------	----------------------------------

Technical Specification	
Construction	Aluminium Die-Cast Housing
LED Chip	TBC
Input Voltage	220-240 VAC, 50/60Hz
Power Factor	Up to 0.9
Operating Temp	10-50W: -20 to +40°C & 100-200W: -40 to +45°C
Standard	CE & UKCA

\* 10-50W IK07



### 7 Year Gold Warranty

Code	W	Description	Lm	Temp	Weight	Windage	WxHxD (mm)
72030	10	Skyline Omni LED Floodlight	1200	3/4/5000K	0.385Kg	0.01m <sup>2</sup>	100x206x38
72031	20	Skyline Omni LED Floodlight	2400				
72032	15/30	Skyline Omni Wattage Switchable LED Floodlight	1800-3600	3/4/5000K	0.585Kg	0.0185m <sup>2</sup>	135x242x38
72033	30/50	Skyline Omni Wattage Switchable LED Floodlight	3600-6000	3/4/5000K	0.85Kg	0.03m <sup>2</sup>	168x298x39
72034	-	Plug In PIR for Skyline Omni LED Floodlight - (10-50W Versions)	-	-	0.045Kg	0.003m <sup>2</sup>	64x61.3x53.4

### 7 Year Gold Warranty + 2 Year On Site Warranty

72035	50/80/100	Skyline Omni Wattage Switchable LED Floodlight - Symmetric	7840-15680	3/4/5000K	3.325Kg	0.082m <sup>2</sup>	293x405x65
72036	100/120/150	Skyline Omni Wattage Switchable LED Floodlight - Symmetric	15680-23520				
72037	100/150/200	Skyline Omni Wattage Switchable LED Floodlight - Symmetric	15680-31360	3/4/5000K	5.225Kg	0.133m <sup>2</sup>	373x482x69
72038	50/80/100	Skyline Omni Wattage Switchable LED Floodlight - Symmetric, with Photocell Switch	7840-15680	3/4/5000K	3.325Kg	0.082m <sup>2</sup>	293x405x65
72048	100/120/150	Skyline Omni Wattage Switchable LED Floodlight - Symmetric, with Photocell Switch	15680-23520	3/4/5000K	5.225Kg	0.133m <sup>2</sup>	373x482x69
72039	100/150/200	Skyline Omni Wattage Switchable LED Floodlight - Symmetric, with Photocell Switch	15680-31360				
72045	200/250/300	Skyline Omni Wattage Switchable LED Floodlight - Symmetric, Loop in Loop out	31400-47100	3/4/5000K	9.6Kg	0.133m <sup>2</sup>	440x515x77
72052	200/250/300	Skyline Omni Wattage Switchable LED Floodlight - Symmetric, Loop in Loop out, with Photocell Switch	31400-47100				
72040	50/80/100	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric	7840-15680	3/4/5000K	3.325Kg	0.082m <sup>2</sup>	293x405x65
72041	100/120/150	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric	15680-23520	3/4/5000K	5.225Kg	0.133m <sup>2</sup>	373x482x69
72042	100/150/200	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric	15680-31360				
72049	50/80/100	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric, with Photocell Switch	7840-15680	3/4/5000K	3.325Kg	0.082m <sup>2</sup>	293x405x65
72050	100/120/150	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric, with Photocell Switch	15680-23520	3/4/5000K	5.225Kg	0.133m <sup>2</sup>	373x482x69
72053	100/150/200	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric, with Photocell Switch	15680-31360				
72046	200/250/300	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric, Loop in Loop out	31400-47100	3/4/5000K	9.6Kg	0.133m <sup>2</sup>	440x515x77
72054	200/250/300	Skyline Omni Wattage Switchable LED Floodlight - Asymmetric, Loop in Loop out, with Photocell Switch	31400-47100				