

# FirestayLED

CCT 4 colour / 2 wattage switchable


## Integrated LED Fixed / Centre Tilt Downlight

- The market leading Firestay CCT Downlight has received a major facelift for 2024
- Firestay Certification: 30, 60 and 90 minute solid joist ceilings, 30 minute I-Joist & Metal Web ceiling systems
- Front CCT/Wattage switch
- 8 in 1 Fixture, 4 colour temperatures, 2 wattages
- Includes white magnetic bezel
- Part B / C / E compliant
- IC rated up to 350mm insulation
- 60° beam angle
- Fixed Screw Terminal & Lever Tool-Free Terminal options
- Spacer plate options available



|   |  |   |                                       |  |   |                            |   |                                  |
|---|--|---|---------------------------------------|--|---|----------------------------|---|----------------------------------|
| Quality Assured Product Warranty <sup>1</sup><br><b>10 Year</b> | Colour Rendering Index <sup>2</sup><br><b>85</b> | Lumens Maintenance Ratio <sup>3</sup><br><b>L80 B10</b> | Water & Dust Protected<br><b>IP65</b> | I Joist Certified<br><b>Fire Rated</b> | 30/60/90 Minutes Solid Joist<br><b>Fire Rated</b> | Compliant<br><b>Part L</b> | <br><b>Coverable</b> | Operating Hours<br><b>70,000</b> |
|---|--|---|---------------------------------------|--|---|----------------------------|---|----------------------------------|

| Technical Specification |                    |
|-------------------------|--------------------|
| Construction            | Die-Cast Aluminium |
| Driver                  | On Board           |
| LED Chip                | Epistar            |
| Input Voltage           | 220 - 240V         |
| Power Factor            | > 0.9              |
| Operating Temp          | -5°C to +35°C      |
| Standard                | CE & UKCA          |



Fixed Screw Terminal



Lever Tool-Free Terminal

### 10 Year Gold Warranty

| Code    | W   | Description  | Lm      | Temp          | ØxHxBezelxCut Out Ø (mm) |
|---------|-----|--|---------|---------------|--------------------------|
| 08187V2 | 5/7 | LED CCT 4 Way Selectable Colour Switch Downlight<br>Dimmable, Plug & Play, 60° Beam Angle. Fixed Screw<br>Terminal     | 570-830 | 2.7/3/4/6000K | 63x45x82x68              |
| 10510V2 | 5/7 | LED CCT 4 Way Selectable Colour Switch Downlight<br>Dimmable, Plug & Play, 60° Beam Angle. Lever<br>Tool-Free Terminal |         |               |                          |
| 10565   | -   | Satin Magnetic Bezel for above   | -       | -             | -                        |
| 10560   | -   | Chrome Magnetic Bezel for above  | -       | -             | -                        |
| 10561   | -   | Brass Magnetic Bezel for above   | -       | -             | -                        |
| 10562   | -   | Antique Brass Magnetic Bezel for above   | -       | -             | -                        |
| 10563   | -   | Matt Black Magnetic Bezel for above  | -       | -             | -                        |
| 10564   | -   | White Magnetic Bezel for above   | -       | -             | -                        |
| 08193   | -   | White Spacer Plate for above (100mm cut out)   | -       | -             | -                        |
| 08194   | -   | Satin Spacer Plate for above (100mm cut out)   | -       | -             | -                        |
| 08190   | 7   | 7W Firestay CCT Centre Tilt LED Downlight - Dim, P&P,<br>40° Beam Angle - Screw Fix Termination                        | 530-600 | 3/4/6000K     | 95x80x80x80              |
| 08200   | -   | Chrome Magnetic Bezel for above  | -       | -             | -                        |
| 08201   | -   | Brass Magnetic Bezel for above   | -       | -             | -                        |
| 08202   | -   | Antique Brass Magnetic Bezel for above   | -       | -             | -                        |
| 08203   | -   | Matt Black Magnetic Bezel for above  | -       | -             | -                        |
| 08205   | -   | Satin Magnetic Bezel for above   | -       | -             | -                        |
| 08196   | -   | Emergency Pack for Firestay LED Downlights   | -       | -             | -                        |
| 10803   | -   | Smart Universal LED Trailing/Leading Edge Dimmer<br>Module for Firestay LED Downlights                                 | -       | -             | -                        |