


luminaversa

Wattage and CCT Switchable High Bay, adjustable beam angles


- A versatile product to meet all customer needs, 27 options in one High Bay
- Sensor controls (optional) - Zhaga enabled PIR & Microwave
- Selectable Narrow (60°), Medium (90°) or Wide Beam angle (120°)
- Smart Controls enabled with Zhaga 18 socket
- Wattage switchable 60W/80W/100W, 90W/120W/150W, 120W/160W/200W
- Switchable CCT 3000K/4000K/5000K
- High efficiency output up to 160 Lm/W
- Ceiling bracket mounting option (Non-EM version only)
- 1-10V dimmable as standard



Zhaga 18 socket



CCT/Wattage Switch



Beam Angle Selection




Technical Specification	
Construction	Die Cast Aluminium body, Polycarbonate lens
Driver	Sosen
LED Chip	SMD 2835
Input Voltage	220-240VAC, 50 / 60Hz
Power Factor	>0.9
Operating Temp	-20°C to +35°C
Standard	CE & UKCA



Optional infra-red remote control available for microwave & PIR sensor versions.

Quick and easy adjustment for multiple fittings; dimming level, presence detection, light levels & automatic on-off time. Average 15m range.





8 Year Gold Warranty

Code	W	Description	Lm	Temp	Weight	ØxH (mm)
70420	60/80/100	LED High Bay, 3 Beam Angles & Zhaga Socket	9801-15756	3/4/5000K	1.94	251x174
70421	90/120/150	LED High Bay, 3 Beam Angles & Zhaga Socket	14986-24071	3/4/5000K	2.15	273x179
70422	120/160/200	LED High Bay, 3 Beam Angles & Zhaga Socket	20332-31723	3/4/5000K	2.52	300x188
70423	-	Ceiling Mounting Bracket	-	-	-	-
15212	-	Zhaga PIR Sensor	-	-	-	-
15213	-	Zhaga Microwave Sensor	-	-	-	-
15190	-	Casambi Zhaga Socket PIR	-	-	-	-
15192	-	Casambi Zhaga Socket Microwave	-	-	-	-
09164	-	Emergency Pack	-	-	-	-
11522	-	Polycarbonate Reflector for 60/80/100W and 90/120/150W Illumina Versa LED High Bays	-	-	-	-
11523	-	Aluminium Reflector for 60/80/100W Illumina Versa LED High Bays	-	-	-	-
11524	-	Aluminium Reflector for 90/120/150W Illumina Versa LED High Bays	-	-	-	-
11525	-	Reflector Cover for 60/80/100W, 90/120/150W and 120/160/200W Illumina Versa LED High Bays	-	-	-	-
11526	-	Aluminium Reflector for 120/160/200W Illumina Versa LED High Bays	-	-	-	-
11527	-	Polycarbonate Reflector for 120/160/200W Illumina Versa LED High Bays	-	-	-	-
06772	-	Remote Control for 15212/3	-	-	-	-

Lumens based on 4000K